LED Linear Pendant

START FROM HERE

- Make sure POWER is COMPLETELY OFF at the fuse box
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area
- · Wear gloves at all times during this installation
- · Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

Technical Support: 1-855-855-8926

Please Note:

- This Kuzco LED fixture comes with pre-wired LED module(s)
- Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage
- For dimming, an ELV (Electronic Low Voltage) or TRIAC type of dimmer is required
- 120V input

- **1.** Remove fixture from its original package
- 2. Separate backplate (3a) from canopy (2a) by removing canopy decorative nuts (2c)
- **3.** Separate mounting plate (1c) from backplate (3a) by removing backplate decorative nuts (3c)
- **4.** Attach mounting plate **(1c)** to electrical junction box **(1a)** using junction box screws provided **(1e)** in hardware package
- **5.** To change fixture height, push and hold wire gripper (2g), slide wire to desired length and then release wire gripper (2g) to secure
- **6.** Make proper electrical connections (**black** to **hot** "L", **white** to **neutral** "N", **ground** to "**GND**") with wire nuts (**1b**) provided in hardware package and place driver (**4a**) inside canopy (**2a**)
- Align mounting plate screws (1d) with holes on backplate (3a) and secure with backplate decorative nuts (3c). Secure backplate (3a) to mounting surface with screws (1g) and anchors (1f)
- **8.** Align backplate screws (3b) with holes on canopy (2a) and secure with canopy decorative nuts (2c)
- **9.** Fine tone wire length if necessary, by push and hold wire gripper (2g) and then adjust wire to desired length



